# VINGTOR STENTOFON

## SPA-V2 Public Address & General Alarm System

#### FEATURES

- Standalone PA & GA system made for the marine environment
- 19" rack with screw terminals for ship cable network
- Power Amplifiers, 100 V line with alternative power output of 120W, 240W, 400W, 600W
- Provides monitoring of power amplifiers
- 6 zones selection + ALL
- Integrated PA/GA solution in combination with ACM system
- Input for 3 microphone panels
- AUX / Alarm input
- Input from Talk-Back system
- Input from PABX (preselected zones)
- Mains 230VAC/24VDC or 230VAC/230 VAC with auto switch-over (110VAC on request)
- Built-in pre-amplifiers
- Wide set of microphone and alarm panels

#### DESCRIPTION

The SPA-V2 system is specially designed to meet the demands for a cost-effective Public Address & General Alarm system for use on board marine vessels. The system is available in different versions and offers a set of standard and optional features that covers the requirements for a marine PA/GA system for all types of marine vessels.

Each SPA rack supports power output from 120W to 600W. A system can consist of multiple racks to provide needed capacity. The racks can be provided in the following sizes: 12 HU, 16 HU, 20 HU, and 24 HU

The SPA system supports the integrated PA and GA solution. This solution is type approved for Public Address and General Alarm. Together with the ACM system, the SPA system is extremely cost efficient where SPA loudspeaker loops are used together with the integrated ACM units to cover areas where PA and GA are required onboard the marine vessel.


At delivery, the rack is equipped and internally wired according to customer specifications.



#### **TYPE APPROVALS**

The SPA system is tested according to EN60945, and type approved by DNV-GL, RMRS, CCS, RINA, CRS, Lloyd's Register, ABS, and BV.





#### System Units SPA-V2

ITEM NUMBER	DESCRIPTION	ITEM NUMBER	DESCRIPTION
Central Units, Control 3005010079 3005010087 2340130005 2340130005 234013000 1023131400 1023131600 3005010235 3005010235 3005010180 3005010184 3005010184 3005010185 3005010173 3005010173 3005010169 2340120022 3005010168 3005010168 3005010168 3005010168 3005010124 3005010124 3005010127 3005010127 3005010127 3005010123 3005010124 3005010124 3005010124 3005010124	I Units & Amplifiers SPA-120-V2 PA Main Unit, 19" Rack 1X120W VPA Amplifier SPA-240-V2 PA Main Unit, 19" Rack 1X240W VPA Amplifier SPA-400-V2 PA Main Unit, 19" Rack 1X400W VPA Amplifier SPA-600D-V2 PA Main Unit, 1X600W Class-D Amplifier SPA-600D-V2 PA Main Unit, 1X600W Class-D Amplifier EA1400 Exigo Class-D Amplifier 1 x 400W VPA-600 Exigo Class-D Amplifier 1 x 400W VPA-120 Power Amplifier, 120W/100V, 220V AC/24V DC - 3HU VPA-240 Power Amplifier, 240W/100V 220V AC/24V DC - 3HU VPA-240 Power Amplifier, 400W/100V 220V AC/24V DC - 3HU SPA-SHELF SHELF 1-4 for Additional Equipment SPA-SHELF SHELF 1-4 for Additional Equipment SPA-SHELF SHELF 1-4 for Additional Equipment SPA-SWITCH-V2 Monitor with fx Volume Line Selector & Switch SPA-SWITCH-V2 Monitor with fx Volume Line Selector & Switch SPA-SWITCH-V2 Abary Exical Voice Rec Mod 1HU Rack Expansion MR1301 Digital Audio Recorder/Player SPA-REM7 Remote Panel with 7 Start & 1 Stop Button SPA-CIONE Control Board with 4-Way Entertainment 6 Zones SPA-TERM-V2 Terminal Board SPA with 2.5m Cable SPA-EBS-V2 Switching board for emergency PA message SPA-EMS-V2 Switching board for emergency PA message SPA-EMS-V2 Output for voice data recorder SMII-PA PA telephone interface (trunk line needed per PA line) SPA-FAIL Power failure output relay with potential-free contact SPA-UNF-V2 New Switch between 230 AC main & emergency UPS	Announcement & Ala 3005010150 2340110019 2340110020 2340110021 3005020029 3005020023 3005010155 3005010096 3005010096 3005010199 3005010199 3005010195 3005010195 3005010202 3005010202 3005010203 3005020040 3005020040 3005010024	<ul> <li>m Units</li> <li>SPA-M1-V2 PA Panel Single, All-Call, Flush</li> <li>SPA-M6-V2 PA Panel Single with 6 zones, All Call, Dimmer, Flush</li> <li>SPA-M6-D PA Panel Dual with 6 zones, All Call, Dimmer, Flush</li> <li>SPA-M6-D PA Panel Dual with 6 zones, All Call, Dimmer, Flush</li> <li>SPA-M6-D PA Panel Dual with 6 zones, All Call, Dimmer, Flush</li> <li>SPA-M6-D PA Panel Dual with 6 zones, All Call, Dimmer, Flush</li> <li>SPA-M6-D PA Panel Dual with 6 zones, All Call, Dimmer, Flush</li> <li>SPA-M6-D PA Panel Dual with 6 zones, All Call, Dimmer, Flush</li> <li>SPA-M6-D PA Panel Dual with covered and illuminated alarm start</li> <li>and reset button for indoor use</li> <li>SPA-AC6-D Dual Alarm panel with covered and illuminated alarm start</li> <li>ACBOKS Back box for SPA-AC6 panels when wall mounted</li> <li>SPA-W1-V2 Weatherproof PA panel for outdoor use, IP-66</li> <li>SPA-W1AP-V2 Weatherproof PA and alarm panel for outdoor use IP-66</li> <li>SPA-W1AR-D Dual Weatherproof PA and alarm panel with 6 zones for</li> <li>outdoor use, IP-66</li> <li>SPA-W6A4-D Dual weatherproof PA and alarm panel with 6 zones for</li> <li>outdoor use, IP-66</li> <li>P-66 Hand Microphone With Plug, Watertight</li> <li>P-66/10 Hand Microphone With Plug, Watertight</li> <li>SPA-PR0G4-RDF Entertainment Program Selector Dual Failsafe, 4</li> <li>Program Inputs PA A&amp;B with Override</li> <li>ENT-4F Bedside Type Panel with Volume Control and Program Selector, Failsafe</li> </ul>

### 

A100K10688 DATE: 20.2.2020

sales@zenitel.com

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Vingtor-Stentofon and Phontech products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice. ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend: Zenitel – All rights reserved.